

To customers

Thank you very much for using our two-way radios. This product has a newly developed function menu and humanism operation design, making it easy to use. It will meet your requirement by the compact size and reasonable price.

Welcome To Use Our Network Walkie Talkie

MAIN FUNCTION:

- Private Call/Group Call/Member List/Parent Group Call
- Zello Available
- Show Battery Status
- GPS (Online Map)
- SOS function (optional)
- Dialing / Edit Message
- Touch Panel
- Apk Install (Optionla)
- Wifi/bluetooth(optional)
- PTT kibitz function
- List quick search
- Software remote update
- Talk priority setting
- Camera/ Camera Vedio



CONTENTS

Main function

Using tips	01
Open the box and check the device	02
Installing and uninstalling of supplied accessories	03
Installing/removing the battery	03
Installing belt clip	04
Install the earpiece/microphone	04
USB charging port	04
Installing SIM /Memory card	05
Button definition	06
Side key and button	07
Button Definition	07
Network setting	08
Preparation work	09
Basic use	11
4G LTE smart PTT management platform	12
For second level admin	13
Add admin	13
Users assignation details	15
Order management	15

Order list	16
Add order	16
File data	17
For third level admin	18
Group management	18
Add the group first	18
Main group and Sub- group	19
Nested groups definitions	19
Device management	19
Add the device	19
Add the device in bulk	20
Order management	21
Add the order	21
File data	23
Smart PTT dispatch Management Platform	25
Note before login in dispatch management platform	25
Private call	28
Get location	29
Get track	31
Group actual location	32
Set speaker in the map center	33

Create a temporary group	34
SOS System Function.....	37
Local Recording	39
Radio Operate Manu	43
POC	43
Zello	44
Phone dialing.....	45
Message	45
Contacts	45
Camera	45
Gallery	45
Vedio	45
Sound Record	46
File Manager	46
Setting	47

Using tips

Unpacking and checking equipments

• Using tips

Please read the following brief instructions, non-compliance with these rules may cause danger or violate the law.

- Turn off the radio before entering flammable or explosive areas.
- Do not charge or change the battery in flammable or explosive areas.
- Turn off the radio before getting close to the blasting zone or detonator areas.
- Do not use radio whose antenna is damaged, touching of damaged antenna will cause heat injury
- Do not attempt to open the radio; the maintenance work should be done by technical expert only.
- To avoid troubles caused by electromagnetic interference or electromagnetic compatibility, please turn off the radio in places where have the banner “ Do not use wireless equipment”.
- In the car with an airbag, do not put the radio within the scope of the airbag deployment.
- Do not store the radio under the direct sunshine or in hot areas
- When you transmit with the radio, do keep away from its antenna for 5cm at least.
- If the radio appears smelly or smoke, please shut off its power immediately and contact with your local dealer.
- Do not transmit too long, for the radio may heat and hurt the user.

• Unpacking and checking equipments


Open the box and check the device

Please remove the radio carefully from the box. We suggest you check the accessories thoroughly according to our list before discarding the packaging.


Supplied accessories:




Radio Body



Ac adaptor



USB cable




Batter



DC Charger



Belt clip User's manual




Note: The antenna frequency range please refers to the annular label at the bottom of antenna.


• Installing and uninstalling of supplied accessories

Installing/removing the battery

1. Align the top of battery with the corresponding groove on the back of radio, then push the battery up to the radio base along the rail on the back of aluminum shell, until the battery latch locks up.




2. To move the battery, please make sure the radio is closed, push the battery latch up, and then push the battery out from the radio.




Installing belt clip

Press the belt clip case into Radio body.




Install the earpiece/microphone

Reveal(remove it) the mic jack cover, insert the headset into the mic jack.



USB charging port

Open the USB port cover, then insert the USB charger cable to the port.




Installing SIM card /Memory Card


Please insert effective SIM /Memory card before use, make sure the SIM card can be effective in 4G/3G radio.



Remove the battery, lift SIM or Memory socket cover, place SIM / Memory card in the socket in the correct position.

After place the SIM / Memory card, replace the battery.



• Button definition





Turn on / Off

Turn on : Press 2 seconds Red Back Key

Turn oFF : Press 2 seconds and display will show Turn off or reboot .

Adjust Volume

Sidekey : Vol + Vol -

Transmit and Receive

Press sidekey PTT Or PTT in display for transmit . Transmit limited time : 50s and red light wil flash same time . Receiver will receive the voice and Light turn Green .

Group Selection

Short press CH - key on the Top or long press F1 Key .Touch the panle and choose Group list , when confirmed press it into the group .

Member Selection

Short press CH - key on the Top or long press F2 Key .Touch the panle and choose Member list , Go left and confirmed press it into Calling .

Light on / off : Press F2 Key 2 second

Records Replay : click Calling records and can show Recent 10 records

Camera function : short press Camera key for Photo. Long press for camera vedio

Recording Function : Long press Volume - turn on recording function .

Network Setting :

Touch Panel - Setting -More -Cellular Networks - Preferred network type

1.2/3/4G Auto selection

2.4G

3.2/3G

4.2G

5.3G

• Preparation work

Warning

Do not over charge the battery.

If the battery charge is not completed in normal time, please stop charging. The battery may flame, smoke or crack due to an abnormal charging process.

Do not put the battery in a microwave or high pressure container.

The battery may flame, smoke or crack.

Do not expose a broken battery to a flame.

If the battery is broken or has an abnormal odour, please remove the battery from the radio and keep it away from any flammable environments. The battery fluid is extremely flammable.

Do not use abnormal batteries

If the battery is abnormal in odour, colour, shape or in any other form, please remove it from the charger or radio and do not use.

Please only use the standard charger and adaptor

The charger and adaptor has been designed to be used exclusively with the Radio. It ensures safety and reliability when charging the battery.

Charging the Lithium battery

Charge before use.


To reduce electrical emission in the battery, please remove the battery from the radio when not in use and store the battery in a cool dry place. When storing the battery for long periods of time:

Remove battery from the radio.

If possible, fully charge the battery before storage.

Store the battery in a cool dry place (temperature less than 25 Celsius).

1. USB cable connects with AC adaptor and the desk charger, and input the AC adaptor insert to power outlet



2. Insert the battery or the radio with battery to the desk charger


Make sure the battery touches with the charging points

When the charger indicator is red, the battery is charging

When the charger indicator turns to green, the charging is finished

Pull out the battery or the radio with battery from power outlet

4G LTE smart PTT management platform



• Basic use

Turn on: press the power button 2 seconds until the start screen appears.

Turn off: press the power button 2 seconds then the screen will have a prompts: Power off/Reboot, please choose the power off to turn off the radio; choose the Reboot to reboot the radio.

Lock the screen and keypad

Screen locked

When the radio is in standby mode, long press F2 key to lock the screen

When the radio is in standby mode, press F2 key to turn off the screen or the radio will turn off the screen when the radio is idle for a while.

Screen unlocked

Long press F2 key to unlock the screen

Press F2 key to turn on the screen

•4G LTE smart PTT management platform

Click: http://www.tytsmartpoc.com/tyt_en/tyt


Using the account and password to enter in, you will find the interface as below:

For second level admin




Add admin

Click the “Add admin”



Then you will find the following interface:



After filled the admin name/ password and Max terminal No, then click “Save”, then you will find this admin information in the “Admin list”

Admin ID	Admin name	Admin level	Upper admin	Admin password	Createtime	Max terminal No	Resisted Terminal No	Remark	Operations
14		1			2018-07-05	3	3		Modify Delete Assign-the-account Aecycle-the-account

Modify: you can change the name and password

Delete: you can delete this admin, but if this admin has devices or account, you can’t delete it.

Assign-the account: you can assign more terminal account to this admin

Recycle the account: if the admin has accounts not be used, you can recycle these accounts

Users assignation details

You can check the details about the third lever administrator.

Sub-account details Authorized Terminal No 4: Allocated No 3: Allocate-able No 1: Resisted No 3:						
ID	Name	Level	Password	Primary account	Create time	Detail of use
14	01	1			2018-07-05	Resisted No 3 Unresisted No 0 Authorized No 3
Search: Admin ID/Admin name						
Total 1 records, PageNo 1/Total 1 pages						

Authorized No: it means the max terminal quantity which you have assigned

Resisted No: it means the used terminal quantity

Unresisted No: it means the unused terminal quantity

Order management

Order list: all the order lists will be shown in this interface.

Admin approved: it means this order has been approved, and it has been complied

Waiting Admin approval/Waiting allocation admin to approve: it means this order hasn't been complied

Order No	Order type	Previous admin	Operation objects	Order states	Create time	Operations
12	Return the surplusaccount			Admin approved.	2018-07-19	Order-detail
11	Add account			Admin approved.	2018-07-19	Order-detail
6	Expand the valid time	S		Waiting Admin approval.	2018-07-13	Order-detail
5	Add account	S		Waiting allocation admin to approve.	2018-07-13	Order-detail
4	Return the surplusaccount			Admin approved.	2018-07-13	Order-detail
3	Add presold account		USA	Admin approved.	2018-07-13	Order-detail
2	Add account			Admin approved.	2018-07-13	Order-detail

Add order

1. When the account number is not enough:

If the account quantity not enough support your radios quantity. You can add order then ask your upper level administrator to assign the account.

Click "Order management", then click "Add order"

2. Return the surplus account

When the quantity for account has exceed the radios, you can return the accounts to the upper level administrator

3. Renew the account

When your account want to expand the valid time, you need renew the validity period by this order.

The screenshot shows the 'Add Order' form with several annotations:

- 'Add Account' section: 'Add number' field.
- 'Return the surplus account' section: 'The returned number' and 'The unregistered terminal number: 1'.
- 'Renew the account' section: 'Please choose the renew account.' with a dropdown menu showing 'Renew02(S1100002)'.
- 'Please choose the renew time' section: 'months (Please input the integer)' and 'time is 12 months in maximum'.
- 'Save' and 'Back to list' buttons.

Annotations include: 'you can search for the renewal device account or user name' pointing to the 'Account/Username' field, and 'to select the device account to renew' pointing to the dropdown menu.

After that, click "Save", and you will find this order in the "Order list"

When the order type is "Return the surplus account, the previous administrator will approve this order automatic, so that the "order states" will shows "Admin approved", this order is deal with.

When the order type is "Add account or renew the account", you need wait the previous administrator to approve your order.

• File data

You can change the password in this interface

Notice: when you want to delete the device in the device list, you need, you need to ask the first-level administrator to delete.

The screenshot shows the 'Edit Password' form with the following fields:

- 'Old Password' field with a masked password '*****'.
- 'New Password' field.
- 'Confirm New Password' field.
- 'Save' and 'Back to list' buttons.

For third level admin

61	Off Line	4GTest	2019FIFA	111111	30	1	2019	2018-07-17	2019-07-17		Show	Edit	Modify
60	Off Line	Betsy3	4GTest	111111	30	1	2019	2018-07-17	2019-07-17		Show	Edit	Modify
58	On line	Betsy 2	2018FIFA	123456	30	1	2019	2018-07-13	2019-07-13		Show	Edit	Modify
50	On line	Betsy	FIFA	123456	30	1	2019	2018-07-12	2019-07-12		Show	Edit	Modify
34	Off Line	456	0012491	111111	30	1	A01	2018-07-05	2019-07-05		Show	Edit	Modify
33	Off Line	123	0003383	111111	30	1	A01	2018-07-05	2019-07-05		Show	Edit	Modify

Search:

Total 7 records, PageNo 1/Total 1 pages

Group management

Add the group first

as below

The screenshot shows the 'Add Group' form in the '4G LTE Smart Ptt Management Platform' interface. The form includes:

- 'Group Name' field with a note: '*Chinese allowed, while it must less than 6 character'.
- 'Group Members' section with a dropdown menu showing 'LTE(0014018) rck01(rck01)'.
- 'Remark' field.
- 'Save' and 'Back to list' buttons.

Annotations include: 'can add the previous device directly if not add, just save the group' pointing to the 'Group Members' dropdown.

Main group and Sub- group

4G LTE | Smart Ptt Management Platform

AMERICAN01

Nested groups definitions

Choose group: 2019 (16) *Main group can be set as sub group of other groups. this is main group

Sub-groups management

there are sub- groups, When main group talking, all sub-groups can hear, Sub- group A and B can not communication to each other, Sub- group can add more than one main group, which ever main groups transmit, all sub-group can hear. Main group A and B can not communication.

Navigation: << < > >>

Group ID/Group Name: 2019(16), 2019(15), A01(6)

Buttons: Save, Back to list

Nested groups definitions

Every group can be merged into a new group; it can also be merged into a new group separately; or be combined with other subgroups. However, new groups that are combined by sub-groups cannot be merged.

The new group that merged by subgroups has all members of the subgroup.

Device management

Add the device

Note: Only third level admin can add the device, please kindly contact your upper admin for the Account. There are two method to add the device: add one by one and add in bulk.

Add the device one by one:

Account number: 1 *Adding account in Bulk can not exceed 2001

First number: 1 default is 1, do not need change

Password: 111111 if need change, please use the software

GPS Cycle: 30 every 30 seconds to update GPS information to platform

Level: 1 lowest level is 1, higher level can have transmitting priority

Validtime: 2019-08-07 16:35:50 *Valid time is 1 year, if renew, please contact authorize

Remark: remote kill and call prohibition do not choose, every function will cost the data, please choose the function according to your requirement

User functions: Contact list, Check location, Record, Monitor, Remote kill, Group call, Call prohibition, Single call, Group switch, Location, Voice record, To get the group member, The last group, The terminals in private call cannot be called again by third party, All selected functions will consume the data, please open the functions needed.

Default group: 2019-08-07 16:35:50 **Default group ID/Click the list to choose.

Group information: Group ID/Group Name: 1 (15)

choose the group, and it will shows in the left, click the group again, the default group will shows the group ID

Buttons: Save, Back to list

Add the device in bulk

4G LTE | Smart Ptt Management Platform

AMERICAN01

add the device in bulk

ID	Status	Username	Account	Password	GPS	Level	Default group	Created time	Valid time	Remark	Users functions	Edit member list	Operations
32	Offline	LTE	0014018	111111	30	1	TYT01	2019-07-05	2019-07-05		Show	Edit	Modify
31	Offline	NR001	NR001	123456	30	1	TYT01	2019-07-04	2019-07-04		Show	Edit	Modify

Search: Name/Account

Total 2 records, Page 1/Total 1 pages

Buttons: Import device in bulk, Back to previous device list, 选择文件, Import, Download Excel template

Name	Password (Special characters other than the underline "_" can not be included)	Account (Only letter and numbers)	Default Group ID	The Group ID the member in (Use "I" to black multiple Group ID)	User functions (* multiple functions to fill in the corresponding number, separated by a vertical line") [Contact list: 1], [Check location: 2], [Record: 3], [Monitor: 4], [Remote call: 5], [Group Call: 6], [Call prohibition: 7], [Single call: 8], [Group switch: 9], [Location: 10], [Voice record: 11], [To get the group member: 12], [The last group: 13], [The terminals in private call cannot be called again by third party: 14]
xjptest5	111111	XJPTST05	562	562	8 12 13 14
xjptest6	111111	XJPTST06	562	562	8 12 13 14
xjptest7	111111	XJPTST07	562	562	8 12 13 14
xjptest8	111111	XJPTST08	562	562	8 12 13 14
xjptest9	111111	XJPTST09	562	562	8 12 13 14

Order management

Add the order

1. When the account number is not enough

If the account quantity not enough support your radios quantity. You can add order then ask your upper level administrator to assign the account.

Click "Order management", then click "Add order"

4GLTE | Smart Ptt Management Platform

AMERICAN01

Device Management 2

Group Management 3

Order management 2

File data 1

Instruction 3

Add Order

Add Account

Add number: this is the radio number, how many units

Return the surplus account

The returned number: The unregistered terminal number: 7 If you give the customer more account, can recall the account

Renew the account

Please choose the renew account:

Account/Username

Betsy(FIFA)

456(0012491)

123(0003383)

Please choose the renew time:

months (Please input the integer.) *Note: The renew time will start from that date the account is approved and renew time is 12 months in maximum.

2.Return the surplus account

When the quantity for account has exceed the radios, you can return the accounts to the upper level administrator

Add Order

Add Account

Add number:

Return the surplus account

The returned number: 1 The unregistered terminal number: 1

Renew the account

Please choose the renew account:

Account/Username

Share03(Share03)

Share02(Share02)

Share01(Share01)

Please choose the renew time:

months (Please input the integer.) *Note: The renew time will start from that date the account is approved and renew time is 12 months in maximum.

3. Renew the account

When your account want to expand the valid time, you need renew the validity period by this order.

Add Order

Add Account

Add number:

Return the surplus account

The returned number: The unregistered terminal number: 1

Renew the account

Please choose the renew account:

Account/Username

Share02(Share02)

Share03(Share03)

Share01(Share01)

Please choose the renew time:

months (Please input the integer.) *Note: The renew time will start from that date the account is approved and renew time is 12 months in maximum.

After that, click “Save”, and you will find this order in the “Order list”

When the order type is “Return the surplus account, the previous administrator will approve this order automatic, so that the “order states” will shows “Admin approved” , this order is deal with.

When the order type is “ Add account or renew the account” , you need wait the previous administrator to approve your order.

Order list <input type="radio"/> Add order						
Order No	Order type	Previous admin	Operation objects	Order states	Create time	Operations
5	Add account	Shane	Shane01	Waiting allocation admin to approve.	2018-07-13	Order-detail
4	Return the surplusaccount	Shane	Shane01	Admin approved.	2018-07-13	Order-detail

File data

You can change the password in this interface

≡

Edit Password

Old Password

New Password

Confirm New Password

Save

Back to list

Notice: when you want to delete the device in the device list, you need, you need to ask the first-level administrator to delete.

Smart PTT dispatch Management Platform

• Smart PTT dispatch Management Platform

Note: If the Dispatch management platform has registered, The radio will off- line, The same to the radio on and dispatch management off.

we suggested that the Dispatch management account is different with PTT platform.

Note before login in dispatch management platform

1. In the software, turn on the GPS function

4G radio account writing tools (Version : 1.0.0.21)

Account writing types

☐ programming cable account writing

☒ on-the-air account writing Change IP

MEID server IP

Account writing management

dealer password

account ID

password

IP address

☐ New password setting

choose the GPS ON

☒ Private call ☒ GPS on/off ☐ Off line beep

progress

2. The dispatcher should selects the function for “ Check Location” in the platform, so that the dispatcher can get the other radios GPS information.

☒ Contact list ☒ Check location ☒ Record ☒ Monitor ☐ Remote kill ☒ Group call ☐ Call prohibition

Users Functions

☐ Check all

☒ Single call ☒ Group switch ☒ Location ☒ Voice record ☒ To get the group member ☒ The last group

☒ The terminals in private call cannot be called again by third party

*All elected functions will consume the data, please open the functions needed.

3. The radio should selects the function for “ Location” in the platform, and the radio should be outdoors to get the location. Also the programming software should be open the GPS

☒ Contact list ☒ Check location ☒ Record ☒ Monitor ☐ Remote kill ☒ Group call ☐ Call prohibition

Users Functions

☐ Check all

☒ Single call ☒ Group switch ☒ Location ☒ Voice record ☒ To get the group member ☒ The last group

☒ The terminals in private call cannot be called again by third party

*All elected functions will consume the data, please open the functions needed.

Current group ID *This project is added by clicking on the items in the selected group.

Set the IP address and GOOGLE/Baidu Map , and login in.

4G LTE

Smart PTT Dispatch Management

Account writing types

☐ programming cable account writing

☒ on-the-air account writing Change IP

MEID server IP

Account writing management

dealer password

account ID

password

IP address

☐ New password setting

☒ Private call ☒ GPS on/off ☐ Off line beep

progress

Help Read Write

Communication port Language setup

port Language English

4G LTE

Smart PTT Dispatch Management

dealer's name

IP address

Map Type: ☐ Single map outside China ☒ Single map in China ☐ Baidu map

Language: ☒ English ☐ Chinese

Login successful on


password Change

Ready Cancel

4. After finished Set up, click the login to enter the dispatcher platform. The “P” means that the radio is in this group. When the radio is in the group same as dispatcher, it can receive a group call from dispatcher and transmit a group call to dispatcher.

Notice: the dispatcher will login the default group, if you want to login other group, you need modify the default group.

ID	Statue	Username	Account	Password	GPS	Level	Default group	Created time	Valid time	Remark	Users Functions	Edit member list	Operations
57	On line	57000000	57000000	12345678	30	1	57000000	2018-07-13	2019-07-13		Show	Edit	Modify




Private call

1. Private call, when the dispatcher choose this function, it can transmit anyone in private call.


Operation:

click one radio you want to speak to, then right click, you can find three options: Private call/Get location/Get track









After you choose the private call, Press “PttDown” and you can transmit the radio, and release the “PttDown” to wait for replying. The radio can press “PTT” to reply.

Notice: the continuous transmission maximum time is 50S, when you over 50S, it will exits transmit automatic.



Location in the MAP

Function	Instruction
	 Terminal Box selected, use the Rectangular Box or round box to choose the desired area
	Track replay
	Terminal Location
	Map Zoom-in
	Map Zoom-out

Note: The GPS function only work outside, in the common case, it will open within 1 minutes, the weather will affected.


Get location

Get location, you can know the radio's place.


Operation:

- 1.click one radio you want to speak to, then right click, you can find three options: Private call/Get location/Get track
- 2.After you choose the get location, you can see the radio's location, and it will show the radio's name on the map, when the mouse move to the radio on the map, you can see more details about this radio.

You can also click the  to get location



And if the radio doesn't open the GPS function or the radio doesn't get the location, you will see the following interface:




Get track:


you can check the radio's activity trajectory within a period of time.

Operation:

1. click one radio you want to speak to, then right click, you can find three options: Private call/Get location/Get track

2. After you choose the get location, you can see the radio's trajectory on the map.


You can also click the  to get track



3. Interval: 5/10/20/50S,


It means the radio will uploads the GPS information in the chosen time.

4. The activity trajectory records will be saved one month, and every time you can track the activity trajectory within 24 hours, for example, when the start time is 2018-7-18 14:56:45, the end time should be within 2018-07-18 14:56:46 to 2018-07-19 14:56:44



Group actual location:

You can check all members' location in the group which the dispatcher is located.





Click "Cancel actual location" to exit the group actual location function




Set speaker in the map center:

When one radio is speaking, this radio's location will show in the center of map.

1. Click the “set speaker in the map center” if one radio is speaking, you can see this radio's location in the center of map, and this radio's mark () will rock.



2. Click the “Cancel the setting speaker in the map center” to exit.




Create a temporary group:

You can create a temporary group in the dispatch platform, and when you exit the dispatch platform, the group will remove.


Operation:

1. You can set choose which members you want to add in the group list, and then you can check the temporary group in the right side. Click the “Temporary group call”, then dispatcher presses the PttUp, or other radio press PTT key , only the selected radios can achieve temporary group call.



Notice: if all members in one group need added to the temporary group, you can choose the Group name, just like Group 2.

If all members in this dispatcher need added to temporary group, you can choose the “Select all”






2. You also can use another mention to add a temporary group, click the following the frame






And you will find the following three keys:




Click  key can move the map;


Click  or  can add the member to temporary:

Operations: click  or  then left click the mouse, and circle a range, the radios in this range will add to the temporary group automatically




3. Then you will find the radios in these range will add to temporary group




After finished to finished circle the range, please click  key to exit.

4. If you want to exit the temporary group, click "Cancel temporary group call"




If you want to remove one of members in the temporary group, please click the member name, the member name would become blue, then click "remove"



If you want to disband this temporary group, please click “remove all”

SOS System Function:

Click Radio top **SOS** Key 3 Seconds . Then Dispatcher Interface will received SOS small window and the account which one calling , Picture as follow :




In the radio display also will show




Local Recording:

1. Click  key




Then you will find the following interface:



Ensure the function has marked is chosen

2. Click the “Local recording”



3. If you have communication records, you will find these call list:

Number	Caller	Called one	Call type	Call time	Call duration	Voice recording file
71	Shane02	Shane03	Private call (Call in)	2018-07-19 14:26:51	6s	D:\VoData\Record\20180719\us7-20180719-142651-Sha
70	Shane02	Shane03	Private call (Call in)	2018-07-19 14:26:09	5s	D:\VoData\Record\20180719\us7-20180719-142609-Sha
69	Shane02	Shane03	Private call (Call in)	2018-07-19 14:25:37	1s	D:\VoData\Record\20180719\us7-20180719-142537-Sha
68	Shane02	Shane03	Private call (Call in)	2018-07-19 14:25:30	6s	D:\VoData\Record\20180719\us7-20180719-142530-Sha
67	Shane03	Shane03, Shane02	Private call (Call out)	2018-07-19 14:24:54	4s	D:\VoData\Record\20180719\us7-20180719-142454-Sha
66	Shane03	Shane03, Shane02	Private call (Call out)	2018-07-19 14:24:51	2s	D:\VoData\Record\20180719\us7-20180719-142451-Sha
65	Shane03	Group2	Group call (Call out)	2018-07-19 14:24:44	1s	D:\VoData\Record\20180719\us7-20180719-142444-Sha

4. Select the Call type/Caller/Call time, then click “Search”, then you will find the records.

5. Replay:

You can double click the record to replay or click the record and click “Replay” to replay

Call type	Private call(Call out)	Caller	Call time	2018-07-19 00:00:01	To	2018-07-19 23:59:59	Search	Replay	Export
<input type="checkbox"/>	Number	Caller	Called one	Call type	Call time	Call duration	Voice recording file(Red means that the file		
<input type="checkbox"/>	1	03	03, 01	Private call(Call out)	2018-07-19 11:25:49	2s	D:\PocData\Record\20180719\us7-20180719-112549-S		
<input type="checkbox"/>	2	03	03, 01	Private call(Call out)	2018-07-19 11:25:51	1s	D:\PocData\Record\20180719\us7-20180719-112551-S		
<input type="checkbox"/>	3	03	02, 01	Private call(Call out)	2018-07-19 11:33:38	1s	D:\PocData\Record\20180719\us7-20180719-113338-S		
<input type="checkbox"/>	4	03	03, 02	Private call(Call out)	2018-07-19 14:24:51	2s	D:\PocData\Record\20180719\us7-20180719-142451-S		
<input type="checkbox"/>	5	03	03, 02	Private call(Call out)	2018-07-19 14:24:54	4s	D:\PocData\Record\20180719\us7-20180719-142454-S		

Local recording disk(H:).Total space 46 GB,available 35 GB,available percentage 76.09%

Call list

0 s

Local recording disk(D:), Total space 46 GB, available 35 GB, available percentage 76.09%

6. Export:


Tick the records and then click the “Export”

Call type	Group call(Call in)	Caller	Shane02	Call time	2018-07-19 00:00:01	To	2018-07-19 23:59:59	Search	Replay	Export
<input checked="" type="checkbox"/>	Number	Caller	Called one	Call type	Call time	Call duration	Voice recording file(Red means that the file			
<input checked="" type="checkbox"/>	1	02	Group2	Group call(Call in)	2018-07-19 09:48:41	1s	D:\PocData\Record\20180719\57-20180719-094841-S			
<input checked="" type="checkbox"/>	2	02	Group2	Group call(Call in)	2018-07-19 09:48:43	3s	D:\PocData\Record\20180719\57-20180719-094843-S			
<input checked="" type="checkbox"/>	3	02	Group2	Group call(Call in)	2018-07-19 09:48:46	3s	D:\PocData\Record\20180719\57-20180719-094846-S			
<input checked="" type="checkbox"/>	4	02	Group2	Group call(Call in)	2018-07-19 09:51:21	2s	D:\PocData\Record\20180719\57-20180719-095121-S			
<input checked="" type="checkbox"/>	5	02	Group2	Group call(Call in)	2018-07-19 09:51:28	4s	D:\PocData\Record\20180719\57-20180719-095128-S			
<input checked="" type="checkbox"/>	6	02	Group2	Group call(Call in)	2018-07-19 10:53:03	4s	D:\PocData\Record\20180719\57-20180719-105303-S			
<input checked="" type="checkbox"/>	7	02	Group2	Group call(Call in)	2018-07-19 10:53:09	3s	D:\PocData\Record\20180719\57-20180719-105309-S			
<input checked="" type="checkbox"/>	8	02	Group2	Group call(Call in)	2018-07-19 10:53:15	14s	D:\PocData\Record\20180719\57-20180719-105315-S			
<input checked="" type="checkbox"/>	9	02	Group2	Group call(Call in)	2018-07-19 11:15:17	4s	D:\PocData\Record\20180719\57-20180719-111517-S			
<input checked="" type="checkbox"/>	10	02	Group2	Group call(Call in)	2018-07-19 11:15:43	2s	D:\PocData\Record\20180719\57-20180719-111543-S			
<input checked="" type="checkbox"/>	11	02	Group2	Group call(Call in)	2018-07-19 11:15:53	2s	D:\PocData\Record\20180719\57-20180719-111553-S			
<input checked="" type="checkbox"/>	12	02	Group2	Group call(Call in)	2018-07-19 11:15:57	7s	D:\PocData\Record\20180719\57-20180719-111557-S			
<input checked="" type="checkbox"/>	13	02	Group2	Group call(Call in)	2018-07-19 11:17:20	2s	D:\PocData\Record\20180719\57-20180719-111720-S			
<input checked="" type="checkbox"/>	14	02	Group2	Group call(Call in)	2018-07-19 11:17:23	8s	D:\PocData\Record\20180719\57-20180719-111723-S			
<input checked="" type="checkbox"/>	15	02	Group2	Group call(Call in)	2018-07-19 11:18:21	17s	D:\PocData\Record\20180719\57-20180719-111821-S			
<input checked="" type="checkbox"/>	16	02	Group2	Group call(Call in)	2018-07-19 15:53:11	2s	D:\PocData\Record\20180719\57-20180719-155311-S			

Radio Operate Manu

• Radio Operate Manu

POC
Zello
Phone dialing
Message
Contacts
Camera
Gallery
Vedio
Sound Record
File Manager
Setting





POC



Click Icon of POC on Radio Interface .
Use Account and password which you already registered in
Radio platform.
Click middle key for PTT
You can click other features for more operation



Click or side up  to your local location infomations and search others location
Click Poc Setting key for other more informations





Zello

Click Zello APP on interface of radio . and log in / off your account for use.
Please go to Zello official website apply for one If you didnt Use it before !



Phone



Same operate with our Smart phone : input phone number or choose a contacts informations and click the green key  and Red key  for dialing and cancel.

Message



Same operate with our Smart phone : input phone number or choose a contacts informations edit the message sending to.

Contacts



Click the + Key and input the numbers to save the contcats name and phone number or other informations .

Camera/Vedio



Touch the camera key on interface into photo. this camera pixel: Front 2Million Rear 5/8 Million Long press the sidekey of camera into Vedio . finally the vedio will be save in the file manager.

Gallery




When you take photos or pictures and save in Gallery . Then you can touch the Gallery to checking picture

Sound Record




Touch the Sound record key into function :



Press Done save in intro File Manager . Press Discard remove .

File Manager



Checking the storage in the file manager . select some useless APP or documents keep storage enough . ensure radio use smooth , also you can find any download files or app in dile manager.

Move it to SD card or add to others bookmarks .

Settings

Click setting we can find 4 kind of name

Wireless & Network

Wlan / wifi

Bluetooth

Data usage

Others wireless and network procedure

Device

Status bar

Display

Sound & notification

Storage

Battery

Apps

Personal

Security

Language and input keypad

System

Date and time

About Phone

Specifications

Size		
	Size (mm)	122*58*26 mm (L x W x H)
	Weight (g)	129
Standard Configuration		
	Chipset	Qualcomm MSM8909 quad-core processor
	Band(MHZ)	2G: GSM 850/900/1800/1900MHz
		2G: CDMA 1X
		3G: WCDMA B1/B5/B8
		3G: TD-SCDMA B34/B39
		3G: EVDO Rev.A 800MHz
		4G: FDD-LTE B1/B3/B5
		4G: TDD-LTE B38/B39/B40/B41
	Sim card	single card single standby
	Message	support
	Physical Button	support
	Sidekey	support
	Onekey PTT	support
	System	Android 5.1.1
	Antenna	GPS / WIFI / Bluetooth Antenna
	Working Voltage	3.7V
	Receive Sensitive	-106dbm
	Max output power	23dBm~25dBm@All up bits
	Working Temperature	-20——+75
	Storage Temperature	-40——+85
	Audio Output	2W@10%

Network		
	4G	FDD LTE, TDD LTE
	3G	WCDMA, TDSCDMA, CDMA2000
	2G	GSM, CDMA
	WIFI	Support Bluetooth
Display		
	Display	2.4inch SPI color display , Pixel : QVGA320*240
	TP	Capacitive screen
Camera		
	Rear	5.000.000 / 8.000.000 (optional)
	Front	2.000.000
Storage		
	Flash	1GB+8GB
	Extended Storage	Micro SD Card (T-FLASH card) Max:32GB
Battery and Connector		
	Capacity(mAh)	4000mAh
	Charger	TBD
	Data cable	USB Micro 5Pin
	Earphone	3.5mm
	Charging mode	charger kit / USB
Others		
	Colors	Black
	Language	English / Chinese

Guarantee

Model Number: _____

Serial Number: _____

Purchasing Date: _____

Dealer: _____ Telephone: _____

User's Name: _____ Telephone: _____

Address: _____ Post Code: _____

Remarks:

- 1 This guarantee card to be kept by the user, no replenishment if lost.
- 2 This guarantee card to be filled & chopped by the dealer, or it is invalid.
- 3 Don't alter the guarantee card, please confirm the serial number on the guarantee card is same as that on the machine.
- 4 One-year guarantee, charger, battery, ear-phone, antenna and cable are not under guarantee.
- 5 The user can get repairing service from the followingways:
 - Go to the shop where you buy the machine.
 - Our local repairing agents.
 - Send back to our company.

Please cut along with this line





RECYCLABLE PACKAGING

4G LTE NETWORK WALKIE TALKIE

USER'S MANUAL



Zello Available



Touch Panel



Dialing



APK Optional