

RA35

FRS 22 Channel

RETCV^{IS}

Feature:

- Auto scan
- Backlight of LCD
- Roger beep
- Monitor select
- Channel select
- Low battery detect
- Call tone select
- Key tone select
- Lock key select
- Call sending
- CTCSS/CDS select
- VOX select
- LED for night light
- Volume adjustment



RA35

FRS 22 Channel

TECHNICAL PARAMETERS

Frequency:	US:FRS
Channel Capacity:	US:22
Output Power:	≤0.5W
Battery type:	4xAAA Alkaline/rechargeable batteries
Antenna type:	Fixed antenna
Battery Voltage:	4.8V/6V
Operating mode:	Half-duplex communication
Temperature range:	-10 ~ +60 Celsius
Size:	152x60x32mm (H*W*D)

RECEIVER

Sensitivity:	-125dBm/<- 119.0dBm
Squelch sensitivity:	-125dBm/<- 123.0dBm
Modulation receiving bandwidth:	6KHz
Intermodulation:	>60dB
Audio distortion:	<5%
Audio power:	>150 <350mW (4.5V)
Spurious response:	>60dB

TRANSMITTER

Output Power:	≤0.5W
Modulation distortion:	< 5% (300- 3000Hz)
Sub-audio bias:	0.3KHz~0.6KHz
Modulation:	FM
Maximum frequency offset:	≤2.5KHz
Maximum current:	≤500mA
Stray radiation:	<-13dBm
Residual modulation:	<-35dB

Package includes:

- 2 x Walkie-talkie
- 2 x Belt Clip
- 1 x User Manual



CE FCC RoHS



Shenzhen Retevis Technology Co.,Ltd.

Add: 7/F, 13-C, Zhonghaixin Science&Technology Park, No.12 Ganli
6th Road, Jihua Street, Longgang District, Shenzhen, China

Web: www.retevis.com

E-mail: kam@retevis.com

Facebook: facebook.com/retevis



MADE IN CHINA