



# RT19&RT619

Portable | Ultrathin fuselage | License free

## Feature :

- |             |                    |                               |
|-------------|--------------------|-------------------------------|
| 1.Monitor   | 5.CTCSS&DCS        | 9.TOT(Time-out Timer)         |
| 2.Key lock  | 6.VOX Function     | 10.Frequency Hopping          |
| 3.Scrambler | 7.Squelch Function | 11.Battery Save Function      |
| 4.Main Mode | 8.Voice Companding | 12.High/ Low Power Selectable |

Two Way Radio

**RETEVIS**

# RT19&RT619

Portable | Ultrathin fuselage | License free

## General

Model Number	RT19&RT619
Frequency Range	US:FRS EU:PMR446
Channel Capacity	US:22CH EU:16CH
Battery Capacity	Li-ion 1300mAh
Working Voltage	DC 3.7V
Antenna Impedence	50Ω
Working temperature	-20-60°C
Weight (Include battery)	90g
Size(Include antenna)	122x50x18mm

## Transmitter

Output Power	US:≤2W EU≤0.5W
Modulation	16K F3E / 11K F3E
Maximum Frequency Deviation	1≤5KHZ / ≤2.5KHz
Remanent Radiation Mode	≤7uW
Electric Current	≤1.2A
Modulation Distortion	≤5% (300-3000Hz)

## Receiver

RF Sensitivity	≤0.25uV / ≤0.3uV
Audio Frequency Power	≥200mW
Audio Distortion	≤5%
Inter-Modulation	≥60dB
Adjacent Channel Selectivity	≥65dB
Spurious Rejection	≥55dB

## Package includes :

2 x Two Way Radio

2 x Battery

1 x Micro-USB cable

2 x Belt Clip

2 x Strap

1 x User manual

CE FCC RoHS



## Shenzhen Retevis Technology Co.,Ltd

Add: 7/F, 13-C, Zhonghaixin Science&Technology Park, No.12 Ganli  
6th Road, Jihua Street, Longgang District, Shenzhen, China

Web: [www.retevis.com](http://www.retevis.com)

E-mail: [kam@retevis.com](mailto:kam@retevis.com)

Facebook: [facebook.com/retevis](https://facebook.com/retevis)



MADE IN CHINA