

# RT75&RT675

FRS 22 Channel & PMR16 Channel

**RETCVIS**

## Feature:

- Adjustable volume level
- Channel Monitor
- Squelch
- Battery save
- Low Battery Alert
- TOT(Time-out Timer)
- Monitor
- Flash light
- Keyboard lock
- CTCSS&DCS
- VOX Function



# RT75&RT675

FRS 22Channel & PMR446 16Channel

## TECHNICAL PARAMETERS

Frequency:	US: FRS	EU: PMR446
Channel Capacity:	US: 22	EU: 16
Output Power:	≤0.5W	
Weight(With battery and back clip):	80g	
Battery Type:	3 A	
Battery Voltage:	3.6V	
Battery Capacity:	600mAh	
Temperature range:	-20 ~ +55 Celsius	
Size:	152x60x32mm(H*W*D)	

## RECEIVER

TIS:	-121
Audio distortion:	≤5% (60%)
Audio power:	≥400mW
Spurious response suppression:	≥60dB
Selectivity:	≥60dB
Modulation receive bandwidth:	±6KHz
Mutual adjustment:	≥55dB

## TRANSMITTER

Output Power:	≤0.5W
Modulation distortion:	<3%
Sub-audio bias:	0.35KHz±150Hz
Modulation:	FM
Maximum frequency offset:	≤2.5KHz
Maximum current:	≤350mA@0.5W
Spurious radiation:	≤-36dBc
Adjacent channel power:	≤-65dBc(12.5KHz)

## Package includes:

- 2 x RT75&RT675 walkie-talkie
- 2 x Belt Clip
- 2 x Lanyard
- 1 x User Manual

CE FC RoHS 

**Shenzhen Retevis Technology Co.,Ltd**

Add: 7/F, 13-C, Zhonghaixin Science&Technology Park, No.12 Ganli  
6th Road, Jihua Street, Longgang District, Shenzhen, China

Web: [www.retevis.com](http://www.retevis.com)

E-mail: [kam@retevis.com](mailto:kam@retevis.com)

Facebook: [facebook.com/retevis](https://facebook.com/retevis)

