

RB628

16CH 0.5W PMR License-free Handheld Two Way Radio Walkie Talkie

Features:

- | | |
|----------------------------------|--------------------------------|
| 1. Time out timer(TOT) | 2. VOX feature |
| 3. Busy Channel Lockout | 4. Keyboard Lock (Auto/Manual) |
| 5. Squelch level(0-9 grades) | 6. Auto power saving function |
| 7. Audio Comband option | 8. Monitor function |
| 9. CTCSS/DCS Encode/Decode | 10. Low power indication/alarm |
| 11. Scan function | 12. Call ringtone (10 group) |
| 13. 2-pin Kenwood accessory port | |

Hot Spot:

- License-free PMR frequency
- 16 channels available
- Designed with VOX hands free, supports PTT push to talk and voice activation talking;
- 1500mAh li-ion battery can last whole day use once be fully charged; low battery alert function helps you keep the walkie talkies always in power
- With 1.28 inch screen and Type-c charging cable (1 on 2)



RB628

16CH 0.5W PMR License-free Handheld Two Way Radio Walkie Talkie

Specification:

Frequency Range	446.00625~446.19375MHz (RX & TX)
Memory Channel	16 CH
Operation Voltage	DC3.7V \pm 10%
Battery Capacity	1500mAh (li-ion)
Step frequency	12.5KHz
Working time (5:5:9)	12 Hours
Antenna Impedance	50ohm
Item Dimensions	105*52*21 mm
Weight	body 82.7g battery 38.3g total 128g (include battery, belt clip)

Electrical Properties:

GENERAL		TRANSMITTER		RECEIVER	
Frequency Rang	446.00625~446.19375Mz	Output power	0.5 W	RF sensitivity	\leq 0.25uV
Channel capacity	16 CH	Adjacent channel power	\geq 60dB	Opening sensitivity	\leq 0.20uV
Working Voltage	3.7 V	TX current	\leq 1.35A	Audio output	\geq 300mW
Antenna impedance	50 Ω	Spurious radiation	\leq 7.5 μ W	Receive current	\leq 410 mA
Step frequency	12.5KHz	Modulation limited	\leq 2.5kHz	Waiting current	\leq 20mA

Standard Accessories:

2* RB628 Two Way Radio
2* Li-ion Battery
2* Belt Clip
1*USB Charging Cable
1*User Manual



Shenzhen Retevis Technology Co.,Ltd.

7/F, 13-C, Zhonghaixin Science&Technology Park, No.12 Ganli
6th Road, Jihua Street, Longgang District, Shenzhen, China
Web:www.retevis.com
E-mail:kam@retevis.com
Facebook:facebook.com/retevis



MADE IN CHINA