

RT22S

FRS License-free 22 Channel
Two Way Radio

RETCV^{IS}

Feature :

- English Annunciation
- VOX
- TOT
- Battery Save
- Squelch
- Scramble/ Compandor
- CTCSS/DCS
- Scan
- Emergency Alarm
- Busy Channel Lockout
- Channel Display
- Battery indicator
- Low Battery Warning



RT22S

FRS License-free 22 Channel Two Way Radio

General:

Operating Frequency:	FRS
Output Power:	≤2W
Channels:	22
Modulation Type:	FM (F3E)
Antenna:	Integrated Antenna
Antenna Gain:	1.8dBi
Bandwidth:	12.5KHz/25KHz
Power Source :	DC3.7V
Dimension:	136*56*21mm

Transmitter:

The maximum deviation:	≤±5KHz
Residual radiation:	<60Db
Current:	≤1000Ma

Receiver:

Sensitivity:	<0.16μV (12dB SINAD)
Squelch Sensitivity:	<0.2μV
Intermodulation:	50dB
Audio Power:	≥300Mw
Current :	≤100mA
Squelch current :	20mA

Package includes :

- 2*RT22S two way radio
- 2*battery
- 2*belt clip
- 2*Micro-USB
- 1*Adapter
- 1*User Manual

CE FCC RoHS 

Shenzhen Retevis Technology Co.,Ltd

Add: 7/F, 13-C, Zhonghaixin Science&Technology Park, No.12 Ganli
6th Road, Jihua Street, Longgang District, Shenzhen, China

Web: www.retevis.com

E-mail: kam@retevis.com

Facebook: facebook.com/retevis



MADE IN CHINA